

[See all 6 Products in Family](#)

## 700nm CWL, 80nm FWHM, 11.8mm Unmounted Diameter



Bandpass Interference Filters

Stock **#46-154** CLEARANCE **20+ In Stock**

MRP ₹2,018

Price inclusive of all taxes

**ADD TO CART**

### Volume Pricing

Qty 1+	₹2,018 each
Need More?	<a href="#">Request Quote</a>

### Product Downloads

### General

Bandpass Filter Type:

### Physical & Mechanical Properties

11.80 ±0.15 Diameter (mm):

>9.2 Clear Aperture CA (mm):

5.10 ±0.5 Thickness (mm):

## Optical Properties

Optical Density OD (Average):

≥3.0

Center Wavelength CWL (nm):

700.00

Center Wavelength CWL Tolerance (nm):

±15

Full Width-Half Max FWHM (nm):

80.00

Full Width-Half Max FWHM Tolerance (nm):

±25

Minimum Transmission (%):

60.00

Coating:

Traditional Coated

Surface Quality:

80-50

Blocking Wavelength Range (nm):

200 - 1200

Angle Sensitivity:

Intended for Collimated Input

## Environmental & Durability Factors

Operating Temperature (°C):

-50 to +75

## Regulatory Compliance

Certificate of Conformance:

[View](#)

Country of Origin:

United States

Imported By:

Edmund Optics India Private Limited  
267, Greystone Building, Second Floor,  
6th Cross Rd, Binnamangala,  
Stage 1, Indiranagar, Bengaluru,  
Karnataka, India 560038  
Phone: +91- 80-6845 0000

## Product Details

- Many CWL Options Available
- Ideal for Biomedical Applications and Instrumentation Integration
- Unmounted and Mounted Versions Offered

Bandpass Interference Filters are used extensively in a variety of biotech, biomedical, and quantitative chemical applications to selectively transmit a narrow range of wavelengths while blocking all others. Interference filters are widely used in instrumentation for clinical chemistry, environmental testing, colorimetry, elemental and laser line separation, flame photometry, fluorescence, immunoassays, etc. In addition, interference filters are used to select discrete spectral lines from arc or gas discharge lamps (Hg, Xe, Cd, etc.) and to isolate a particular line from Ar, Kr, Nd:YAG, and other lasers. Bandpass Interference Filters are often used in conjunction with laser diodes and LEDs. The filters are available with traditional coating and in 11.80 or 12.70mm diameters.

**Note:** Interference filters will function with either side facing the source. We recommend, however, orienting the "mirror-like" side toward the source to minimize any thermal effects. Beam vignetting may be necessary if the source overfills the actual filter area.

## Compatible Mounts